

# DAE-20050

## Driver for High Power Laser Diodes

Compact design Output current: ≤200A QCW or CW operation mode USB communication Water cooling circuit included Up to 45V compliance Voltage No extra supply voltage required Differential current input signal available Laser temp sensor & PHD input signals Reverse current protected.



### Technical data

### Specifications Output current

≤ 200 A Max. compliance voltage 45 V Min. compliance voltage 10 V ≤ 50 V Supply voltage 1 Max. output power <sup>2</sup> 9000 W Max. power dissipation allowed4 250W Rise time 3 < 22 us Fall time 3 < 22 us Max. pulse width 4 CW

#### Output signals

Current monitor 10 mV/A TTL 5V Trigger out Trigger out delayed TTL 5V TTL 5V Laser on out

### Input signals

TTL 5V Trigger input External current input signal 5 TBD TTL 5V Emergency stop Laser on external TTL 5V TTL 5V Interlock Flow meter <sup>5</sup> I2C / TTL USB 2.0 / RS485 5 Connectivity NTC, 10kΩ @25°C Laser temperature sensor

#### Mechanics

Input water cooling tube 6 4 x 6 mm > 14 °C Water cooling temp Weight 500 g Dimensions 130x75x35 mm 15 to 60°C Operating temperature 7

- 1. Aprox. 6V above the compliance voltage. The minimum feeding voltage is 14V.
- 2. Instant Power. Maintaining the Heat Sink temperature below 45°C.
- 3. Test conditions: VLD-=6V, I=200A. Lower rise and fall time available. Please, contact us.
- 4. The CW operation is allowed  $\leq$  60A, VLD-  $\leq$  4V, with 21° water refrigeration.
- Under development.
- 6. Internal x external tube diameter.
- 7. Temperature measured by internal sensor.

### Description

The DAE-20050 is a compact and powerful laser diode driver. Current waveforms can be CW, modulated or pulsed up to 200A.

This driver includes a 32bit  $\mu C$  with an USB 2.0 communication port. Commands allow the full control of the driver features (pulse generation, current level, temperature limits, pulse's counter...) while keeping a great amount of information thanks to all the signals available (current level, voltage, photodiode, temperatures, delayed trigger for syncs...).

The DAE-20050 has been designed thinking in high power applications. An internal water circuit is embedded in the bases for high demanding applications.

# Block diagram

